

A6650 Android SmartPOS PDA



Logistic & Warehousing



Hospitality & Retail



Law Enforcement





Android 12 Powered by Uniphiz



PCI PTS 6.x SRED



6.5" IPS Display



13MP AF + 2MP AF Dual-Rear Camera





SPECIFICATIONS

00	Operating System	Android 12 Based (GMS certified) with Uniphiz support
₿	Processor	Qualcomm Quad core A53 2.0GHz
	Memory	LPDDR4 4GB+eMMC 64GB
	Card Readers	MSR ICCR Contactless Native Android NFC (Reader, Card Emulation)
Ø	Cameras	Front Camera: 5MP FF Dual-Rear Camera: 13MP AF + 2MP AF
	Displays	2480*1080 Pixel 6.5inch IPS LCD, Multi-touch,AF
((†))	Comms Configurations	4G Cellular Dual-Band Wifi ® (2.4/5GHZ) Bluetooth® 5.0
Ī	Battery	Li-ion Polymer 3.8V 5400mAh Field Replaceable
	Barcode	Zebra SE4100 Barcode Scanner
SAM	SIM / SAM	1SAM+2SIM+1SD eSIM
(*) *)	Sensor	Light Sensor G-Sensor Vibration Motor Flashlight GPS
Ę	Keys / Buttons	Power (Finger ID) Volume + Volume - Scan
IJ,ŵ)	Audio	Audio Speaker Dual Mic Receiver
	Ports	1xUSB Type-C 1x Pogopin (2PIN)
Ĵ	Adapter	18W PD fast charging 5V3A/8V2A/12V1.5A
[D]	Physical	172 x 81 x 16.5mm Weight (g) : 372g
\bigcirc	Durability	IP rating: IP67 Drop Test: 1.5M ESD: 15KV contact, 18KV Air
භු	Accessories(opt)	Wrist Band Modular Charging Kit
Č	Environmental	5% ~ 96% Relative Humidity, Non-condensing -10 ~ 50°C Operating Temperature -20°C ~ 70°C Storage Temperature
\bigcirc	Certifications	PCI6 PTCRB GMS AMEX DPAS JCB PAYPASS PAYWAVE qUICS InteactFlash EMV L1 EMV CL L1 FCC IC CE UKCA BQB RoHS









This document is provided to you for informational purposes only. All features and specifications are subject to change without notice. PAX and the PAX logo are either trademarks or registered trademarks of **PAX Technology Inc**. The **Bluetooth**® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by **PAX Technology Inc**. Is under license. Other trademarks and trade names are those of their respective owners. © 2023 **PAX Technology Inc**. All rights reserved.

